

EM-EV-CLR-12V - Voltage monitoring device



2903246

<https://www.phoenixcontact.com/us/products/2903246>

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



The EV Charge Lock Release monitors the 12 V operating voltage of the electrically driven plug locking actuator, routes locking and unlocking signals, and sends an unlocking pulse to the actuator when the operating voltage fails.

Commercial data

Item number	2903246
Packing unit	1 pc
Minimum order quantity	1 pc
Product key	XWB555
Catalog page	Page 61 (C-7-2019)
GTIN	4046356728843
Weight per piece (including packing)	133.6 g
Weight per piece (excluding packing)	124 g
Country of origin	DE

EM-EV-CLR-12V - Voltage monitoring device



2903246

<https://www.phoenixcontact.com/us/products/2903246>

Technical data

Product properties

Product type	Voltage monitoring relay
Product family	CHARX control advanced
Application	Locking release module in the event of mains failure for AC charging controllers for commercial applications (EU)
Operating mode	Stand-Alone
Charging standard	Type 2
Charging mode	Mode 3

System properties

Charging controllers

Number of charging points	1
---------------------------	---

Electrical properties

Type of charging current	AC 3-phase
Locking release in the event of mains failure	Integrated release function of the locking actuator for disconnection of Infrastructure Plug and Infrastructure Socket Outlet

Supply

Supply voltage	12 V DC $\pm 5\%$
Supply voltage range	12 V DC $\pm 5\%$
Max. current consumption	4 mA (in idle state)
Current carrying capacity	≤ 4 A

Input data

Digital

Number of digital inputs	1
Frequency range	50 Hz ... 60 Hz
Nominal power consumption	< 0.5 W (No-load)
Nominal current I_N	approx. 5 mA
Nominal input voltage U_N	12 V
Input voltage range U1	-3 V ... 3 V (Off)
Input voltage range U2	-30 V ... -10 V (Locking ON)
Input voltage range U3	10 V ... 30 V (Unlocking ON)

Output data

Switching

Output name	Relay output OUT+/-
Minimum switching capacity	46 VA
Maximum switching voltage	approx. 11.5 V (Operating/capacitor voltage minus the diode voltage of ~ 0.5 V)

EM-EV-CLR-12V - Voltage monitoring device



2903246

<https://www.phoenixcontact.com/us/products/2903246>

Max. switching current	4 A
Current carrying capacity	≤ 4 A

Dimensions

Width	35.6 mm
Height	90 mm
Depth	61.00 mm

Environmental and real-life conditions

Ambient conditions

Degree of protection	IP20
Ambient temperature (operation)	-25 °C ... 60 °C
Ambient temperature (storage/transport)	-25 °C ... 60 °C

Approvals

Conformity/Approvals

Conformance	CE-compliant
-------------	--------------

Standards and regulations

Standards

Standards/regulations	IEC 61851-1
	EN 61000-6-2
	EN 61000-6-3

Mounting

Mounting type	DIN rail mounting
Mounting position	any

EM-EV-CLR-12V - Voltage monitoring device



2903246

<https://www.phoenixcontact.com/us/products/2903246>

Classifications

ECLASS

ECLASS-12.0	27144703
ECLASS-11.0	27144703
ECLASS-13.0	27144703

ETIM

ETIM 9.0	EC002889
----------	----------

UNSPSC

UNSPSC 21.0	39121800
-------------	----------

EM-EV-CLR-12V - Voltage monitoring device



2903246

<https://www.phoenixcontact.com/us/products/2903246>

Environmental product compliance

EU RoHS

Fulfills EU RoHS substance requirements	Yes
Exemption	7(a), 7(c)-I

China RoHS

Environment friendly use period (EFUP)	EFUP-10
	An article-related China RoHS declaration table can be found in the download area for the respective article under "Manufacturer declaration". For all articles with EFUP-E, no China RoHS declaration table issued and required.

EU REACH SVHC

REACH candidate substance (CAS No.)	Hexahydromethylphthalic anhydride(CAS: n/a)
	Lead(CAS: 7439-92-1)
SCIP	3e1dadb2-2907-4480-90e1-38d7ddcecef8

EM-EV-CLR-12V - Voltage monitoring device



2903246

<https://www.phoenixcontact.com/us/products/2903246>

Accessories

EM-CP-PP-ETH - AC charging controller

2902802

<https://www.phoenixcontact.com/us/products/2902802>



EV charge control is used to charge electrical vehicles on the 3-phase AC mains power supply according to IEC 61851-1 Mode 3. All necessary control functions are integrated. Additional functions are available for various charging applications.

STEP-PS/ 1AC/12DC/1 - Power supply unit

2868538

<https://www.phoenixcontact.com/us/products/2868538>



Primary-switched STEP POWER power supply for DIN rail and direct mounting, input: 1-phase, output: 12 V DC/1 A

Phoenix Contact 2024 © - all rights reserved

<https://www.phoenixcontact.com>

Phoenix Contact USA
586 Fulling Mill Road
Middletown, PA 17057, United States
(+717) 944-1300
info@phoenixcon.com