

#### Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of NFE31ZT471F1E9# from the official website of Murata

Ticase download the latest datasheet of NT E512147 IT 1E5# from the official websit

http://www.murata.com/en-us/products/productdetail?partno=NFE31ZT471F1E9%23

"#"at the end indicates the package specification code.

In Production





NFE31ZT471F1E9L



< List of part numbers with package codes >

NFE31ZT471F1E9B

NFE31ZT471F1E9K

NFE31ZT471F1E9L




## **Applications**

Lineviteble	Diagon has a use to used and commit with		
Unsuitable	Please be sure to read and comply with		
Applications	these "Precautions for use."		
Specific Applications	Automotive infotainment/comfort		
	equipment,Consumer equipment,		
	Medical equipment [GHTF A/B/C]		
	except for implant & surgery & auto		
	injector,Industrial equipment except for		
	transportation & facility & energy		
	equipment		
	Please refer to Our Website and		
	specifications, etc. for information about		
	the performance, functions, quality,		
	management, and safety required for		
	the above applications, and use		
	Products after confirming the		
	performance and reliability of the actual		
	Product.		
Recommended	Automotive infotainment/comfort		
Applications	equipment		



## Appearance & Shape







: Electrode (in mm)



## Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
K	330mm Embossed Tape	8000
L	180mm Embossed Tape	2000



### **Features**

The chip "EMIFIL" NFE31ZT is a small size T-type circuit EMI suppression filter.

#### Features

- Its large rated current of 6A and low voltage drop due to small DC resistance are suitable for DC power line use.
- 2. The feedthrough capacitor realizes excellent high frequency characteristics.
- 3. The structure incorporates built-in ferrite beads which minimize resonance with surrounding circuits.
- 4. 22 to 2,200pF lineups can be used in signal lines.

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





## NFE31ZT471F1E9L

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of NFE31ZT471F1E9# from the official website of Murata

"#"at the end indicates the package specification code.



## **Specifications**

Shape	SMD
Size Code (in inch)	1206
Length	3.2mm
Length Tolerance	±0.35mm
Width	1.6mm
Width Tolerance	±0.15mm
Thickness	1.6mm
Thickness Tolerance	±0.15mm
Operating Temperature Range	-40°C to 85°C
Mass(typ.)	0.034g
Number of Circuit	1
Rated Current	6A
Rated Voltage	25Vdc
Withstanding Voltage	62.5Vdc
Insulation Resistance(min.)	1000ΜΩ
Capacitance	470pF
Capacitance Tolerance	50/-20%
Size Code (in mm)	3216

2 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



# NFE31ZT471F1E9L


Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.


Please download the latest datasheet of NFE31ZT471F1E9# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=NFE31ZT471F1E9%2

"#"at the end indicates the package specification code.








**Insertion Loss Characteristics** 

Insertion Loss Characteristics (Main Items)



**Equivalent Circuit** 

3 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

