

PSB-600 Series (3 Phase) Specifications











Features:

- Multiple overload/ short circuit protection modes
- Efficiency above 92%
- Easy parallel connection for more power
- Small size
- DIN rail mountable
- Cooling by free air convection
- UL508 (industrial control equipment) approved
- EN60950-1
- Built-in DC OK relay contact
- 3 year warranty

OUTPUT

JT	Cat. No.	PSB-60024
	DC VOLTAGE	24 V
	RATED CURRENT	25 A
	CURRENT RANGE	Refer to Output derating curve
	RATED POWER	600 W
	RIPPLE & NOISE (max)	100 mVp-p
	VOLTAGE ADJ. RANGE	Ripple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1µF & 47µF parallel capacitor.
	VOLTAGE TOLERANCE	-0.03
	VOLINGE FOLLIVINOL	Tolerance: includes set up tolerance, line regulation and load regulation.
	START UP WITH STRONG LOAD	≤ 50,000 μF
	CURRENT SHORT CIRCUIT Icc	60 A
		Max 2 sec.: Hiccup mode
		Permanent: Continuous mode
	DISSIPATION POWER LOAD mas	28 W
	LINE REGULATION	± 0.5%
	LOAD REGULATION	± 1%
	SETUP, RISE TIME	1 sec. (max)
		Length of set up time is measured at cold first start. Turning ON/OFF the power supply may lead to increase of the set up time.
	HOLD UP TIME (Typ.)	Typ. 20 msec
	VOLTAGE RANGE	330 ~ 550V AC
	FREQUENCY RANGE	47 ~ 63 Hz +-6%

INPUT

VOLTAGE RANGE	330 ~ 550V AC
FREQUENCY RANGE	47 ~ 63 Hz +-6%
EFFICIENCY (Typ.)	>92 %
AC CURRENT (330 - 500 Vac.)	0.95 - 0.85 A
INRUSH CURRENT (Typ.)	< 17 A < 5 msec
INTERNAL FUSE	T 6.3 A
EXTERNAL FUSE (recommended)	16 A (MCB curve B)

PROTECTION

LEAKAGE CURRENT	< 1.5 mA @ 500 Vac
OVERLOAD	In (60°C) x 1.5 3 3 min.; Current max. Overload @ 4Vdc (permanent) Imax=In (60°C) x (1.8 \sim 2.2)

OVER VOLTAGE OVER TEMPERATURE SHORT CIRCUIT PROTECTION

DC OK AKTIV SIGNAL (max.)

Yes. Shuts down output and automatically restarts when the temperature inside goes down 1 Hiccup Mode / 2 Fold Back / 3 Restart After Main

ENVIRONMENT

WORKING TEMP.	-25 up to +70 °C
	(>60°derating 2.5% °C)
HUMIDITY	95 % at 25°C, no condensation
STORAGE TEMP	-40 up to +85 °C
TEMP. COEFFICIENT	$\pm 0.03\%$ / C° (0 ~ 60 °C)
VIBRATION	In according to IEC60068-2-6

 $20 \sim 30 \text{ Vdc}$

SAFETY & EMC


	g
SAFETY STANDARDS	UL508 approved, IEC/EN 60950, EN 50178, IEC/EN 60950, EN60950-1, PELV EN 60204-1
WITHSTAND VOLTAGE	I/P-O/P: 3k VAC
PROTECTION CLASS	IP 20 (EN/IEC 60529)
ISOLATION RESISTANCE	100 MΩ (min) @ 500 Vdc
EMI CONDUCTION & RADIATION	EN61000-6-4
HARMONIC CURRENT	EN61000-3-2
EMS IMMUNITY	EN 61000-4-2, EN 61000-4-3, EN 61000-4-4, EN 61000-4-5,
	EN 61000-4-6, EN61000-6-2, EN61000-6-4,
	The power supply is considered a component which will be installed into a final equipment. The final equipment must be
	re-confirmed that it still meets EMC directives.


OTHERS

MTBF IEC 61709	> 500.000 h
POLLUTION DEGREE	2
CONNECTION TERMINAL BLOCK	2.5 mm Screw (24 ~ 14 AWG)
DIMENSION	85x120x140 mm (3.34x4.72x5.51 in)
PACKING	0.75 kg (1.9 lbs) each
NOTE	All parameters NOT specially mentioned are measured at 230V AC input, rated load and 25°C of ambient temperature.



Mechanical Specification





TB1 Terminal Pin. No Assignment


Pin No.	Assignment (3 phase)
1	L1
2	L2
3	L3
4	FG 🖶
5	FG 🖶

TB2 Terminal Pin. No Assignment


Assignment
DC output -V
DC output +V
DC OK relay contacts

DC OK Relay Contact

Outputs are used for preventive function monitoring of the power supply. An electrically isolated signal contact is available. The signal contact closes when the output power is OK and opens when the output voltage falls below 20Vdc $\pm 5\%$.




Output Derating Curve



Parallel Connection

A parallel connection with the same model power supply can be set up to increase the output power. The output has to be adjusted approximately to the same value (± 20mV) while applying a 1-2 A load to all devices before connecting them in parallel. In PSA-600xx, for more power, the position of the Easy Parallel jumper needs to be changed to enable a parallel connection. In this mode up to 4 power supplies can be put together in parallel.





Note: All dimensions are in millimeters, to convert to inches multiply by 0.03937.

OSC Class 2 Series

PSA Flex Serio

PSB FIEX Series

PS-S Slim Series

os Low Profile Ser

os Industrial Serie

PS C & W Series

CBI Type

CB Type Chargers

Accessories

Appendix