


GS1A THRU GS1M

SURFACE MOUNT GENERAL RECTIFIER
Reverse Voltage - 50 to 1000 Volts Forward Current - 1.0 Ampere



Dimensions in inches and (millimeters)

FEATURES

- The plastic package carries Underwriters Laboratory Flammability Classification 94V-0
- For surface mounted applications
- ◆ Low reverse leakage
- Built-in strain relief.ideal for automated placement
- High forward surge current capability
- High temperature soldering guaranteed: 250°C/10 seconds at terminals
- ◆ Glass passivated chip junction

MECHANICAL DATA

Case: JEDEC DO-214AC molded plastic body over passivated chip

Terminals: Solder plated, solderable per MIL-STD-750,

Method 2026

Polarity: Color band denotes cathode end

Mounting Position : Any

Weight: 0.002 ounce, 0.07 grams

MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Ratings at 25°C ambient temperature unless otherwise specified.

Single phase half-wave 60Hz, resistive or inductive load, for capacitive load current derate by 20%.


TWGMC Catalog Number	SYMBOLS	GS1A	GS1B	GS1D	GS1G	GS1J	GS1K	GS1M	UNITS
Maximum repetitive peak reverse voltage	VRRM	50	100	200	400	600	800	1000	VOLTS
Maximum RMS voltage	VRMS	35	70	140	280	420	560	700	VOLTS
Maximum DC blocking voltage	Vpc	50	100	200	400	600	800	1000	VOLTS
Maximum average forward rectified current at T∟=110°C	I(AV)	1.0						Amp	
Peak forward surge current 8.3ms single half sine-wave superimposed on rated load (JEDEC Method)	Ігѕм	30.0							Amps
Maximum instantaneous forward voltage at 1.0A	VF	1.1							Volts
Maximum DC reverse current TA=25°C at rated DC blocking voltage TA=100°C	lR	5.0 50.0						μΑ	
Typical junction capacitance (NOTE 1)	Сл	15.0						pF	
Typical thermal resistance (NOTE 2)	Reja	75.0						°C/W	
Operating junction and storage temperature range	ТЈ,Тѕтс	-50 to +150						°C	


Note:1.Measured at 1MHz and applied reverse voltage of 4.0V D.C.


2.P.C.B. mounted with 0.2x0.2"(5.0x5.0mm) copper pad areas




RATINGS AND CHARACTERISTIC CURVES GS1A THRU GS1M

















The cruve graph is for reference only, can't be the basis for judgment(曲线图仅供参考)!